



### Features

- Secondary service transformer 1000 VA, protected by thermomagnetic circuit breakers
- Voltage presence indicator (optional), sensing range 30 to 600 VAC
- Secondary service wiring made with harnesses
- Lock-holder in cabinet
- Door locking with screw clamps
- Interchangeable flanged connection

### Specifications

System	3 phases 4 wires
Voltage	240 - 480 VCA
Capacity	70, 150, 250 o 400, 630 AMP.
Control voltage	120 - 240 VCA
Enclosure	Metal NEMA 4, gray ANSI 61
Actuating lever	Industrial use with door lock and padlock holder



### Spare parts (suggested)

Code	Description
101CKTK-R-3	Fuse protection for control transformer
M5250M	120 VCA duplex outlet
26BAH1303F	2 phases 3 wires 220 VCA. half turn socket
DS-1020-G	Lid for receptacle 30 mm for outdoor use
DS-70-G	Cover for duplex receptacle for outdoor use

Equipment code	Receptacle and outlet	Dimensions	Aprox. weight
MPCPE480703R1	Standard passage box 70 AMP. 480 VCA.A	30" x 15" x 12"	61.72 lbs
MPCPE4801503R1	Standard passage box 150 AMP. 480 VCA.A	30" x 15" x 12"	66.13 lbs
MPCPE4802503R1	Standard passage box 250 AMP. 480 VCA.A	40" x 23" x 15"	77.16 lbs
MPCPE4804003R1	Standard passage box 400 AMP. 480 VCA.A	40" x 23" x 15"	88.18 lbs
MPCPE4806303R1	Standard passage box 630 AMP. 480 VCA.A	40" x 23" x 15"	88.18 lbs

Note: Stainless steel cabinet, receptacles and outlets of your choice are available upon request.  
If you have any questions, please contact our sales department at **(871) 731 89 41**.